



## R600X5

The PRIME R600X5 is a 5-channel amplifier designed to run an entire car audio system! The R600X5 produces up to 75 Watts into each of its four channels with a dedicated subwoofer channel capable of producing 300 Watts into 2-Ohms

### SPECIFICATIONS

Number of Channels: 5  
 Rated Power: 50 Watts x 4 +  
 200 Watts x 1 @ 4-Ohms  
 75 Watts x 4 +  
 300 Watts x 1 @ 2-Ohms  
 Total Power: 600 Watts RMS  
 Dynamic Power: 58 Watts x 4 +  
 224 Watts x 1 @ 4-Ohms 0° Res  
 95 Watts x 4 +  
 403 Watts x 1 @ 2-Ohms 0° Res  
 Crossover Controls: *Front/Rear*: High-Pass/Low-Pass 50-250Hz  
*Sub*: Low-Pass variable 50Hz – 250Hz  
 Suggested Alternator: 75 A  
 Average Current Draw: 35 A  
 Max Current Draw: 70 A  
 Recommended Fuse : 80 A  
 Dimensions: 1.98" x 6.77" x 13.19

### FEATURES

- Remote Punch Level Control – Sub Channel
- RCA and High level Input with 2/4/5 Channel Select
- 12dB/octave Butterworth crossover
- On Board Punch EQ Control
- Separate Front, Rear and Sub Gain Control
- Real time output and power supply thermal sensing
- Cast aluminum heatsink
- 4 Gauge power/ground connectors
- MOSFET power supply
- Over current protection
- Short circuit protection
- Muted turn on

### PARTS