

SONY

5.2 A/V Receiver



SPECIFICATIONS

4 Ohm/8 Ohm Switching: Yes (6 ohm)
Auto Tuning: Yes
Direct Tuning: Yes (via remote)
Preset Channel (FM/AM): 30 FM, 30 AM
Analog Audio In: 2 (not including AV in)
Coaxial Input: 1
Optical In: 2
Headphone Out: Yes
AV In: Including Front AV: 2
HDMI In: 4
Composite Video Out: Inc. Monitor Out: 1
HDMI Out: 1
BRAVIA® SYNC™
Dimension (WxHxD inches): 17 x 6-1/4 x 13
Receiver Weight: 16 lb 61oz

PARTS

Remote	1-492-049-11
Mic	1-542-830-11
Loop Antenna	1-754-741-11
Manual	4-448-428-12
Front Panel Assy	X-2586-107-1
Power Cord	1-837-308-11
Tuner Assy	A-1846-564-A

- 5.2 Channel A/V Receiver (145W/ ch x 5)
- 4 HDMI Inputs /1 out with 3D & 4k pass through
- 4k Pass Through
- iPod/iPhone Playback via USB
- Digital Cinema Auto Calibration for Quick Speaker Set-Up
- HD Digital Cinema Sound for movie theater like experience
- Dolby® TrueHD and dts® HD Enhanced Audio Codecs
- Fully Assignable inputs allows for use of all connections