

STRDN1050

7.2 A/V BLUETOOTH WIFI RECEIVER



- 7.2 Channel 1155W A/V Receiver (165W x 7 @ 8 ohms)
- Built-in Wi-Fi® for easy access to Music
- Stream music from your iPhone®/iPad®, iTunes® or compatible Apps with AirPlay®
- Built-in Bluetooth® for music streaming from your smart phone or tablet
- 10 HD Inputs (8 HDMI™, 2 Component)
- 4K Pass-through and Upscale
- Legendary Sound
- Sound Optimizer let's you hear all sound effects at any volume
- MHL connection to mobile phones
- HD Digital Cinema Sound™ with Front-High speakers (HD DCS)
- 2nd Zone output
- Control with your iPhone® or Android™ devices with free Apps
- 3D Ready
- Advanced Digital Cinema Audio Calibration for Quick Set-Up
- Dolby® TrueHD, Pro logic IIz and dts® HD Enhanced Audio Codecs
- iPod®/iPhone® music and video playback with charging via USB
- Audio Return Channel uses just one cable for TV audio
- Standby pass-through of Audio & Video via HDMI™ connected devices
- Fully Assignable inputs allows for use of all connections
- BRAVIA® Sync for multi-device control w/ one remote
- 24p True Cinema™ pass-through

STRDN1050

7.2 A/V BLUETOOTH WIFI RECEIVER

SPECIFICATIONS

MHL (Mobile High-definition Link) Front/Rear: 2 (1 Front / 1 Rear)
 60ohms, 1kHz, 1ch driven) THD: 0.9%
 (60ohms, 1kHz, 2ch driven) THD: 1%
 60ohms, 1kHz, 1ch driven: 165 W
 60ohms, 1kHz, 2ch driven: 120 W + 120 W
 6ohms, 20-20kHz, 2ch driven: 100 W + 100 W (0.09%)
 Auto Tuning: Yes (GUI)
 Direct Tuning: Yes (GUI)
 Preset Channel (FM/AM): 30 FM, 30 AM
 Station Name: Yes
 Assignable Component Video In: Yes
 Auto Standby: Yes
 Digital Input Assign: Yes (Component/Optical/Coax)
 Display: 10 digit dot matrix
 Easy Automation: Yes Custom Preset
 GUI: Yes w/GUI Blending
 Analog Audio In: 4 (not including AV in)
 Coaxial: 1
 Multi-ch In: Yes (FM and AM)
 Optical In: 2
 Headphone Out: Yes (Gold)
 Pre Out (Subwoofer): 2
 Bluetooth: Yes (Bluetooth version 2.1+EDR Profile: A2DP, AVRCP Ver1.3 Codec: SBC/aptX/AAC) with NFC
 Ethernet (Switching HUB): 1
 USB: Yes 2 (Front:iPhone/WM)(support format: MP3, AAC, WMA, WAV192k, Flac 192k, ALAC, AIFF and DSD (2.8MHz)) support iPhone4s spec: (DC 5V, 1.0 A MAX)
 AV In: Including Front AV: 2
 Component Video In: 2 (assignable)
 Component Video Out: 1
 HDMI In: 6 (1 front)
 AV Out: Inc. Monitor Out: 1 Component Out
 Composite Video Out: Inc. Monitor Out: 1
 HDMI Out: 3
 Receiver Dimension (WxHxD inches): 16.9 x 6.77 x 12.97
 Weight: 22.1 lbs

PARTS

1-492-706-11 REMOTE COMMANDER (RM-AAU189)
 1-542-830-11 MEASUREMENT MIC (MONO)
 1-754-741-21 LOOP ANTENNA (AM loop antenna (aerial))
 1-793-184-41 CONNECTOR (F TYPE ADAPTOR) (FM wire antenna (aerial))
 1-490-558-72 BLUETOOTH MODULE
 A-1846-564-A TUNER1AMF ASSY
 1-837-308-11 CORD, POWER-SUPPLY
 1-828-311-61 WIRE (FLAT TYPE) (9 CORE)
 X-2588-819-1 FRONT PANEL ASSY
 4-442-859-01 KNOB, MENU
 4-442-860-01 KNOB, VOLUME

