

SONY®



SPECIFICATIONS

- Max power output: 100 watts x 4 at 4 ohms
Speaker Impedance: 4-8 Ohms
- Audio Format(s) Supported:
MP3/WMA/WAV/AAC/FLAC files
- Band: AM / FM
- Station Preset(s): 18 FM / 12 AM
- Preout Impedance: 220 ohms
- Preout Voltage: 5 volt
- Tuner Type: Digital Clarity Tuner with RDS
- CD: CD, CD-R/RW
- Tilt Range: 0-45° mounting angle
- Text Displayed: Source, artist, track, playback time, menu, clock, Pandora® and Bluetooth® data
- Text Lines: 2 line s of information
- 12V Trigger Output(s): Power remote on
- Antenna Terminal(s): AM/FM Antenna Input Terminal
- Audio In: Front: AUX input
Rear: SiriusXM Input
- Infrared Port: Wireless remote
- RCA Audio Output(s): Front, Rear, and Subwoofer RCA pre-amp outputs
- Remote Jack: Optional wired remote terminal
- USB Port(s): Front
- NFC: Yes
- Bluetooth Secure Simple Pairing: Yes
- Bluetooth Version: Bluetooth Version 3.0
- Dimensions (Approx.): 178 x 50 x 178 mm, 7.125 x 2 x 7.125 inch (w/h/d)
- Weight (Approx.): 1.3 kg (2 lb. 13 oz.)

MEX-XB100BT

AM/FM/CD Receiver w/Bluetooth

Enjoy wireless Bluetooth® connectivity with NFC to stream music, make hands-free calls through your receiver.

FEATURES

- Hi-power 100 watt x 4 Digital Amp (40W x 4 CEA RMS wattage)
- Stream music wirelessly w/Bluetooth® & NFC connection
- Advanced sound with EQ10, MEGA BASS, and HPF/LPF crossovers
- CD-R/RW playback includes MP3/WMA/AAC/WAV/FLAC
- Bluetooth® Auto Pairing for iPhone®/iPod®
- Siri Control for hands-free control via your iOS device
- Hands-free music playback and control (Android™ and iOS devices)
- Works with Pandora (iOS and Android™)
- SiriusXM™ Satellite radio connector ready
- SongPAL App for intuitive remote control
- Intuitive Quick-BrowZer® and Jump Mode search features
- Front Aux input and USB with High-Charge
- 5-Volt front, rear, and sub RCA preamp outputs
- Subwoofer direct connection capable
- Digital Clarity Tuner with RDS
- Steering wheel remote control input ready
- Convenient wireless remote supplied (RM-X231)
- External hands free mic supplied

SONY®



MEX-XB100BT

AM/FM/CD Receiver w/Bluetooth

SPECIFICATIONS

- 1-542-986-11 MICROPHONE UNIT
- 3-934-325-21 SCREW, +K (5X8) TAPPING (1 piece)
- 1-848-738-11 CABLE FOR AUTOMOBILE (12P)(Connection cable)
(US, CND,
- 9-885-202-40 FUSE (BLADE TYPE) (AUTO FUSE) (15 A/32 V)
- 1-848-736-11 CABLE FOR AUTOMOBILE (POWER)
- 4-461-753-01 COLLAR
- 4-276-003-02 KEY (FRAME) (1 piece)
- X-2583-962-1 FRAME ASSY, FITTING
- 1-489-810-42 REMOTE COMMANDER (RM-X231)
- 4-563-800-41 OPERATION INSTRUCTION
- 1-848-738-11 CABLE FOR AUTOMOBILE (12P)
- 1-848-736-11 CABLE FOR AUTOMOBILE (POWER)
- X-2591-157-1 KNOB (VOL) (SV) ASSY (Including NFC module)
- 1-848-787-11 MICROPHONE, CONNECTION CABLE
- 9-885-202-40 FUSE (BLADE TYPE) (AUTO FUSE) (15 A/32 V)
- A-2070-676-A PANEL (SV) ASSY, FRONT
- 1-846-819-51 CABLE FLEXIBLE FLAT (27 CORE)
- 1-754-945-11 BT, ANTENNA
- A-2066-255-A MAIN BOARD, COMPLETE
- X-2590-421-1 PANEL ASSY, SUB
- A-2070-676-A PANEL (SV) ASSY, FRONT