



## Bose Lifestyle 38 IV Euro Region 4 Home Theater System Product Information Guide

### Features:

- Direct Reflecting dual cube speaker arrays
- Built-in Dolby® Digital and DTS® decoding
- Bose® Videostage® 5 steering circuitry, for surround sound from VHS, stereo, and mono sources
- VS-2 Video Enhancer with HDMI & video upscaling
- uMusic™ intelligent playback system stores up to 200 hours of music
- 20 AM/20 FM presets
- Multibrand-for-video RF remote
- Bose® link for easy connection to a Bose® system in another room
- Adapt IQ - Equalizes Audio to optimize acoustic output after installation
- 115/230 v Dual Voltage System



### Specifications:

- 1 video input/1 video output (composite, S-video, and component—component video requires included adapters(2))
- Inputs and switching for 4 audio sources (4 analog, 4 coaxial digital, 1 optical digital)
- Stereo analog output
- Digital outputs: 1 optical, 1 coaxial
- Media center • 3 3/4"H x 15 3/4"W x 11 1/2"D • (9.4 x 39.9 x 29.2 cm) • 9 lbs
- Cube speakers • 6 1/4"H x 3"W x 4"D • (15.7 cm x 7.9 cm x 10.2 cm) • 2.4 lbs
- Center-channel speaker • 3 1/8"H X 6 1/4"W X 4 1/8"D • 7.9 cm H x 15.9 cm W X 10.5 cm D) • 2.36 lbs (1.07 kg)
- Acoustimass® module • 13"H X 8"W X 21 5/8"D • (33 cm H X 20.3 cm W X 54.9 cm D) • 26.22 lbs (11.9 kg)

### Parts & Accessories

Description	Part Number
• Main Console	307535-121F
• Double Satellite Cubes	192420-119
• Base Module	278799-619
• Remote	270606-012
• Speaker Cables (L,C,R)	180643-4
• Speaker Cables (RS,LS)	180644
• Console Power Pack	256764-007
• Base Module P/Cord	258491-001
• Bose U-Link Cable	276865-001
• FM Antenna	148589
• AM Antenna	199824-002
• Adapt IQ Kit	279100-001
• TV Power Sensor	258359
• Owners Manual	289328-001
• Essentials Kit	274493-002